



**WACKER
NEUSON**
all it takes!

GP4000A

5100070504

[Home](#) >> [Catalog](#) >> [Products](#) >> [Power](#) >> [Portable Generators](#) >> [GP4000A](#)

GP4000A

Material number 5100070504

4,000 Watt portable generator with wheel kit. Powered by a Honda engine.



Product details

Wacker Neuson™ portable generators are perfect to keep job site running smoothly. Designed for construction and rental, these quiet high performance generators deliver reliable power in a rugged, compact package

- Powered by Honda engine and paired with Mecc Alte alternator to provide reliable, clean and consistent power
- Selectable voltage setting allows for maximum power usage
- Auto idle control reduces the engine to lower speed when no load is detected, saving on fuel and extending machine life
- High impact polyethylene fuel tank and heavy-duty shock mounting combined to provide outstanding impact protection
- Solid wheels and flip-up handle provide for easy and convenient transport on the job site and in the shop

Comes with

- Operator's Manual

Technical specifications

GP4000A

OPERATING FLUIDS

Fuel consumption (Prime load)	0,6 GPH US
Run Time (Prime Load)	12,5 std

MECHANICAL DETAILS

Length	523 mm
Width	698 mm
Height	612 mm
Operating weight	75,3 kg
Dry Weight	53,5 kg

OPERATING FLUIDS

Fuel consumption (Prime load)	2,4 L/Std
Run Time (Prime Load)	12,5 std

ENVIRONMENT DATA

Sound level LpA	72,0 dB(A)
-----------------	------------

GENERATOR

Insulation class	H
------------------	---

Output frequency	60 Hz
Voltage accuracy	6,0 %
Generator specification	Brushless
Phase	1 ~
Continuous Output	3.800 W
Efficiency factor 1~	1,00 cos
Voltage 1~	240 V, 120 V
Maximum Output	4.000 W

GENERATOR

Insulation class	H
Output frequency	60 Hz
Voltage accuracy	6,0 %
Generator specification	Brushless
Phase	1 ~
Continuous Output	3.800 W
Efficiency factor 1~	1,00 cos
Voltage 1~	240 V, 120 V
Maximum Output	4.000 W

ELECTRICAL SYSTEM

Receptacle Type	NEMA5-20R,Duplex GFCI,125V,20A, NEMAL14-30R,TL,125/250V,30A, NEMAL5-30R,TL,125V,30A
Breaker Switch On/Off	1 Pole
Number of Sockets	4
Circuit Breaker Amperage AC	18 A

ENGINE

Engine type	Gasoline engine
Cylinder	1
Cylinder capacity	16,5 Inch3
Engine Manufacturer	Honda
Engine Designation	GX270
Kraftstofftyp	Gasoline
Oil filling max.	0,3 gal US
Operating Engine speed	3.600 1/min
Starter type	Recoil starter

ELECTRICAL SYSTEM

Receptacle Type	NEMA5-20R, Duplex GFCI, 125V, 20A, NEMA14-30R, TL, 125/250V, 30A, NEMA5-30R, TL, 125V, 30A
Breaker Switch On/Off	1 Pole
Number of Sockets	4
Circuit Breaker Amperage AC	18 A

ENVIRONMENT DATA

Sound level LpA	72,0 dB(A)
-----------------	------------

ENGINE

Engine type	Gasoline engine
Cylinder	1
Cylinder capacity	270 cm3
Engine Manufacturer	Honda
Engine Designation	GX270
Kraftstofftyp	Gasoline
Oil filling max.	1,10 l

Operating Engine speed	3.600 1/min
Starter type	Recoil starter

MECHANICAL DETAILS

Length	20,6 "
Width	27,5 "
Height	24,1 "
Operating weight	166,0 lb
Dry Weight	117,9 lb

Please Note

This product availability can vary from country to country. It is possible that information / products may not be available in your country. More detailed information on engine power can be found in the operator's manual; the started power may vary due to specific operating conditions. Subject to alterations and errors expected. Applicable also to illustrations.

Copyright © 2023 Wacker Neuson SE